

## Sample Sysprep.inf file for Microsoft Windows Server 2003 using Altiris Deployment Solution tokens

```
;SetupMgrTag
[Unattended]
    OemSkipEula=Yes
    InstallFilesPath="C:\Sysprep\i386"
;Leave following setting null if deleting pagefile.sys from image
    KeepPageFile=
    OemPnPDriversPath=

[GuiUnattended]
    AdminPassword=*
    EncryptedAdminPassword=No
    OEMSkipRegional=1
    OEMDuplicatorstring="Sysprep"
    TimeZone=20
    OemSkipWelcome=1
    AutoLogon=Yes
    AutoLogonCount=1

[GuiRunOnce]
Command0="c:\windows\system32\deltree /Y c:\sysprep"
Command1="regedit.exe /s c:\dell\script\srcpath.reg"

[Display]
    BitsPerPel = 16
    XResolution = 1024
    YResolution = 768
    VRefresh = 60

; If not using Deployment Solution tokens, replace the data in the section below using percentage signs with
normal data
[UserData]
    ProductKey=%PROD_LIC%
    FullName=%CONTACT%
    OrgName="Company XYZ"
    ComputerName=%SERIALNUM%

[LicenseFilePrintData]
    AutoMode=perseat
;AutoMode=PerServer
;AutoUsers=1000

[TapiLocation]
    AreaCode=512
```

## Building a Single Image for Dell PowerEdge Servers Using Altiris Deployment Solution, continued

```
[Identification]
```

```
JoinWorkgroup=WORKGROUP
```

```
[Networking]
```

```
InstallDefaultComponents=Yes
```

```
[SysprepMassStorage]
```

```
;Adaptec Embedded Serial ATA HostRAID Controllers
```

```
PCI\VEN_8086&DEV_24DF=%systemdrive%\dell\storage\aarich.inf", "\", "Adaptec Embedded Serial ATA HostRAID Controller", "Adaptec Embedded Serial ATA HostRAID Driver Ver 6.00 For Windows 2000/XP/2003"
```

```
PCI\VEN_8086&DEV_25B0=%systemdrive%\dell\storage\aarich.inf", "\", "Adaptec Embedded Serial ATA HostRAID Controller", "Adaptec Embedded Serial ATA HostRAID Driver Ver 6.00 For Windows 2000/XP/2003"
```

```
PCI\VEN_8086&DEV_2652&SUBSYS_01801028=%systemdrive%\dell\storage\aarich.inf", "\", "Adaptec Embedded Serial ATA HostRAID Controller", "Adaptec Embedded Serial ATA HostRAID Driver Ver 6.00 For Windows 2000/XP/2003"
```

```
PCI\VEN_8086&DEV_2652&SUBSYS_01851028=%systemdrive%\dell\storage\aarich.inf", "\", "Adaptec Embedded Serial ATA HostRAID Controller", "Adaptec Embedded Serial ATA HostRAID Driver Ver 6.00 For Windows 2000/XP/2003"
```

```
;Adaptec Ultra160 SCSI Controllers
```

```
PCI\VEN_9005&DEV_00C0=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 39160 - Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_00C0&SUBSYS_F6209005=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 39160/3960D - Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_00C0&SUBSYS_F6200E11=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 39160D Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_0080=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 29160 - Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_0080&SUBSYS_E2A09005=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 29160 Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_0080&SUBSYS_E2A00E11=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 39160D Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_0080&SUBSYS_62A09005=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 29160N - Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_0080&SUBSYS_E2209005=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec SCSI Card 29160LP Low Profile Ultra160 SCSI", "u160dsk1"
```

```
;Adaptec Ultra160 ASIC Controllers
```

```
PCI\VEN_9005&DEV_008F=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec AIC-7892 - Ultra160 SCSI", "u160dsk1"
```

```
PCI\VEN_9005&DEV_00CF=%systemdrive%\dell\storage\ADPU160M.INF", "\", "Adaptec AIC-7899 - Ultra160 SCSI", "u160dsk1"
```

```
;Adaptec Ultra320 SCSI Controllers
```

```
PCI\VEN_9005&DEV_801D=%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
```

```
PCI\VEN_9005&DEV_801E=%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
```

```
PCI\VEN_9005&DEV_801F=%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
```

## Building a Single Image for Dell PowerEdge Servers Using Altiris Deployment Solution, continued

```

PCI\VEN_9005&DEV_800F="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec Ultra320 Family
  Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_800F&SUBSYS_005F9005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8000&SUBSYS_00609005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8010&SUBSYS_00409005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8011&SUBSYS_00419005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8012&SUBSYS_00429005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8014&SUBSYS_00449005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8015&SUBSYS_00409005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8016&SUBSYS_00409005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"
PCI\VEN_9005&DEV_8017&SUBSYS_00449005="%systemdrive%\dell\storage\9g\scsi-nonraid\ADPU320.INF", "\", "Adaptec
  Ultra320 Family Manager Set - Microsoft Disk", "u320dsk1"

```

```

;LSI Logic FC9XXX Fibre Channel Adapters

```

```

PCI\VEN_1000&DEV_0621="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic FC909 Fibre Channel
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0622="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic FC929 Fibre Channel
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0624="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic FC919 Fibre Channel
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0626="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic FC929X Fibre Channel
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0628="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic FC919X Fibre Channel
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0030="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic 1020/1030 Ultra320 SCSI
  Adapter", "symmpi.tag"
PCI\VEN_1000&DEV_0032="%systemdrive%\dell\storage\symmpi.inf", "\", "LSI Logic 1035 Ultra320 SCSI
  Adapter", "symmpi.tag"

```

```

;DELL CERC SATA 1.5/6ch

```

```

PCI\VEN_9005&DEV_0285&SUBSYS_02911028="%systemdrive%\dell\storage\cercsr6.inf", "\", "DELL CERC SATA 1.5/6ch
  storage Controller", "DISK1"

```

```

;DELL 438

```

```

PCI\VEN_8086&DEV_1960&SUBSYS_11121111="%systemdrive%\dell\storage\oemsetup.inf", "\", "Dell PERC 2/SC storage
  Controller", "SOURCE_DISK"

```

```

;DELL 466

```

```

PCI\VEN_8086&DEV_1960&SUBSYS_11111028="%systemdrive%\dell\storage\oemsetup.inf", "\", "Dell PERC 2/SC storage
  Controller", "SOURCE_DISK"

```

## Building a Single Image for Dell PowerEdge Servers Using Altiris Deployment Solution, continued

```

PCI\VEN_8086&DEV_1960&SUBSYS_09A0101E="%systemdrive%\dell\storage\oemsetup.inf", "\", "Dell PERC 2/SC storage
  Controller", "SOURCE_DISK"
PCI\VEN_8086&DEV_1960&SUBSYS_11111111="%systemdrive%\dell\storage\oemsetup.inf", "\", "Dell PERC 2/SC storage
  Controller", "SOURCE_DISK"

;DELL 467
PCI\VEN_8086&DEV_1960&SUBSYS_04671028="%systemdrive%\dell\storage\oemsetup.inf", "\", "Dell PERC 2/DC storage
  Controller", "SOURCE_DISK"

;Dell PERC 2, 2/Si, 3/Si, 3/Di Controllers
PCI\VEN_1011&DEV_0046&SUBSYS_13649005="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 2 RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_0001&SUBSYS_00011028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 2/Si RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_0003&SUBSYS_00031028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Si RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_0002&SUBSYS_00021028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_0002&SUBSYS_00D11028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_0002&SUBSYS_00D91028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_000A&SUBSYS_01061028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_000A&SUBSYS_011B1028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_1028&DEV_000A&SUBSYS_01211028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3/Di RAID
  Controller", "DISK1"
PCI\VEN_9005&DEV_00C5&SUBSYS_00C51028="%systemdrive%\dell\storage\perc2.inf", "\", "Dell PERC 3 RAID (SCSI
  chip)", "DISK1"

;PERC 3/QC (DELL)
PCI\VEN_101E&DEV_1960&SUBSYS_04711028="%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 3/QC storage
  Controller", "SOURCE_DISK"

;PERC 3/DC (DELL)
PCI\VEN_101E&DEV_1960&SUBSYS_04931028="%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 3/DC & PERC
  3/DCL RAID Controller", "SOURCE_DISK"

;PERC 3/SC (DELL)
PCI\VEN_101E&DEV_1960&SUBSYS_04751028="%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 3/SC RAID
  Controller", "SOURCE_DISK"

;PERC 4/Di 0123 (DELL)
PCI\VEN_1028&DEV_000E&SUBSYS_01231028="%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/Di RAID
  Controller", "SOURCE_DISK"

```

## Building a Single Image for Dell PowerEdge Servers Using Altiris Deployment Solution, continued

```
;PERC 4/Di 013B (DELL)
PCI\VEN_1028&DEV_000F&SUBSYS_013B1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4/Di 014A (DELL)
PCI\VEN_1028&DEV_000F&SUBSYS_014A1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4/Di 014C (DELL)
PCI\VEN_1028&DEV_000F&SUBSYS_014C1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4/Di 014D (DELL)
PCI\VEN_1028&DEV_000F&SUBSYS_014D1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4/DC (DELL)
PCI\VEN_1000&DEV_1960&SUBSYS_05181028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/DC RAID
  Controller", "SOURCE_DISK"

;PERC 4/SC (DELL)
PCI\VEN_1000&DEV_1960&SUBSYS_05201028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4/SC RAID
  Controller", "SOURCE_DISK"

;CERC ATA100/4ch (DELL)
PCI\VEN_101E&DEV_1960&SUBSYS_05111028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL CERC ATA100/4ch RAID
  Controller", "SOURCE_DISK"

;PCI-EXPRESS
;PERC 4e/Si (DELL)
PCI\VEN_1028&DEV_0013&SUBSYS_016C1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4e/Si RAID
  Controller", "SOURCE_DISK"

;PERC 4e/Di (DELL)
PCI\VEN_1028&DEV_0013&SUBSYS_016D1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4e/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4e/Di (DELL)
PCI\VEN_1028&DEV_0013&SUBSYS_016E1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4e/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4e/Di (DELL)
PCI\VEN_1028&DEV_0013&SUBSYS_016F1028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4e/Di RAID
  Controller", "SOURCE_DISK"

;PERC 4e/Di (DELL)
PCI\VEN_1028&DEV_0013&SUBSYS_01701028=%systemdrive%\dell\storage\oemsetup.inf", "\", "DELL PERC 4e/Di RAID
  Controller", "SOURCE_DISK"
```

## Building a Single Image for Dell PowerEdge Servers Using Altiris Deployment Solution, continued

```
;PERC 4e/SC (DELL)
PCI\VEN_1000&DEV_0408&SUBSYS_00011028="%systemdrive%\dell\storage\oemsetup.inf","\","DELL PERC 4e/SC RAID
  Controller","SOURCE_DISK"

;PERC 4e/DC (DELL)
PCI\VEN_1000&DEV_0408&SUBSYS_00021028="%systemdrive%\dell\storage\oemsetup.inf","\","DELL PERC 4e/DC RAID
  Controller","SOURCE_DISK"

;PERC5/E Controller Family
PCI\VEN_1028&DEV_0015&SUBSYS_1F011028="%systemdrive%\dell\storage\9g\perc5\oemsetup.inf","\","DELL PERC 5/E
  Adapter RAID Controller","DISK1"

;PERC5/I Controller Family
PCI\VEN_1028&DEV_0015&SUBSYS_1F021028="%systemdrive%\dell\storage\9g\perc5\oemsetup.inf","\","DELL PERC 5/I
  Adapter RAID Controller","DISK1"

;PERC5/i Integrated Controller Family
PCI\VEN_1028&DEV_0015&SUBSYS_1F031028="%systemdrive%\dell\storage\9g\perc5\oemsetup.inf","\","DELL PERC 5/i
  Integrated RAID Controller","DISK1"

;Dell SAS 5x Controllers
PCI\VEN_1000&DEV_0054&SUBSYS_1F041028="%systemdrive%\dell\storage\9g\sas-nonraid\lsi_sas.inf","\","Dell SAS 5x
  Controller Driver (Windows Server 2003 32-bit)","lsi_sas.tag"
PCI\VEN_1000&DEV_0054&SUBSYS_1F061028="%systemdrive%\dell\storage\9g\sas-nonraid\lsi_sas.inf","\","Dell SAS 5x
  Controller Driver (Windows Server 2003 32-bit)","lsi_sas.tag"
PCI\VEN_1000&DEV_0054&SUBSYS_1F071028="%systemdrive%\dell\storage\9g\sas-nonraid\lsi_sas.inf","\","Dell SAS 5x
  Controller Driver (Windows Server 2003 32-bit)","lsi_sas.tag"
PCI\VEN_1000&DEV_0054&SUBSYS_1F081028="%systemdrive%\dell\storage\9g\sas-nonraid\lsi_sas.inf","\","Dell SAS 5x
  Controller Driver (Windows Server 2003 32-bit)","lsi_sas.tag"
PCI\VEN_1000&DEV_0054&SUBSYS_1F091028="%systemdrive%\dell\storage\9g\sas-nonraid\lsi_sas.inf","\","Dell SAS 5x
  Controller Driver (Windows Server 2003 32-bit)","lsi_sas.tag"
```